



Repairing Samsung SPH-A500 Logic Board

Replacing the Samsung SPH-A500 logic board.

Written By: Nick Dominikovic

INTRODUCTION

This is a step by step guide on how to replace the Samsung SPH-A500 logic board.



TOOLS:

- [Phillips #0 Screwdriver](#) (1)

Step 1 — Logic Board



- Turn phone over
- Push the gray tab above the battery forward to remove the battery.

Step 2



- Remove the battery from the phone, which will reveal four screws at the corners of the phone.

Step 3



- Remove all four screws using a small Philips screwdriver.
- Note: The screws do not need to be completely removed from the case, as long as they are unscrewed.




Step 4



- Remove back cover by carefully prying it open.
- Note: Some force may be required.




Step 5



- Pull the side tabs outward while simultaneously lifting up the circuit board.
- Do not completely pull out the circuit board.




Step 6




- Look for the clip at the top right corner of the logic board.

Step 7



- Remove the clip from the logic board.

Step 8



- Remove the logic board.
- Replace the broken logic board with a new one.

<p>To reassemble your device, follow these instructions in reverse order.</p>

This document was last generated on 2014-12-04 12:40:07 AM.